



SNW01 / 02 / 03 | SNWRL3

Smart Tech's RF Switch range delivers reliable wireless switching with self-powered convenience – no wiring or batteries required. Available in 1-, 2-, and 3-way configurations, these wall-mountable switches pair seamlessly with the SNWRL3 receiver module for high-capacity control (up to 1500W resistive loads).

	SNW01W	SNW02W	SNW03W		SNWRL3
Description	1 Way RF Switch	2 Way RF Switch	3 Way RF Switch	Working Voltage	AC90-270V/DC120-300V
Product Size	86x88x15.5mm	86x88x15.5mm	86x88x15.5mm	Receiver Lifetime	Open/Close ≥ 400000
Working Voltage	Self-Powered	Self-Powered	Self-Powered	Resistive Load	≤1500W
Standby Current	0ua	0ua	0ua	Inductive Load	≤1200W
Emission Current	≤30mA	≤30mA	≤30mA	Capacitive Load	≤1200W
Frequency	433.92+/75KHz MHz	433.92+/75KHz MHz	433.92+/75KHz MHz	Standby Power	≤0.3W
Emission Power	≥+13dBm	≥+13dBm	≥+13dBm	Working Power	≤0.8W
Press Life Time	≥300000 times	≥300000 times	≥300000 times	Working Temperature	-20~+70°C
Remote Distance	Outside no obstruction ≥200m, Inside≥50m	Outside no obstruction ≥200m, Inside≥50m	Outside no obstruction ≥200m, Inside≥50m	Working Humidity	≤80%

BROUGHT TO YOU BY:

